

RMX112 12 Channel Mic/Line Rack Mixer

The RMX112 is a 1U rack-mounted 12 channel mixer with 6 mic/line combination inputs and 3 dedicated stereo line inputs. The RMX112 is ideal for compact rack installations and is suitable for use in karaoke, entertainment, classroom, conference and other presentation applications.



Mono Channels:

- 6 Mic/Line inputs (CH1-6)
- XLR/Jack combo connectors
- Input selector switch for Ch1-6: Mic, Phantom, Line
- Low-distortion mic pre-amp with high dynamic range
- +18V Phantom power on each mic Input channel
- Channel level controls
- Input signal LED indicators
- Mic.1 priority mute potentiometer

Stereo Channels:

- 3 Stereo line inputs (CH7&8, 9&10, 11&12)
- RCA (L/R) connectors
- Channel level controls
- Input signal LED indicators



System outputs & controls:

- Stereo line outputs (L+R XLR)
- Mono output and level control (6.35mm Jack)
- Mic.out with activation switch for monitoring CH1-6 outputs (6.35mm Jack)
- Record out (L+R RCA)
- 3 Band EQ for low, mid, high adjustments
- Master output level control
- 4 Segment LED L+R signal level meters
- Operating supply voltage: 220-240V AC or 24V DC
- Dimensions (WxHxD): 483x44x195mm
- Weight: 2.9kg

The specifications above are correct at the time of printing this data sheet. For improvement purposes, all specifications for these units, including design and appearance, are subject to change without prior notice.